



Installation & Operating Manual

With the CaprioSW adapter card you can power up or power down your PC. The device operates the power button circuit of your PC as if you were pushing it.

Installing your CaprioSW

1. Turn off power to the computer and disconnect the power cord. Open the computer cabinet following the manufacturer's instructions.
2. Locate an unused PCI expansion slot and remove the expansion slot cover, save the slot cover screw for later use.
3. Remove the CaprioSW from its packaging. Always handle the adapter by its edges or metal bracket.
4. Insert the card into the PCI expansion slot. Secure the mounting screw.
5. Disconnect the ATX cable from the motherboard and insert the extension cable provided into the motherboard. Connect the ATX cable to other end of the extension cable.
6. Locate the cables from the power button and the two wire taps from the extension cable. Now snap each cable of the power supply button on the taps.
7. Insert the power connector from the extension cable to the back of the CaprioSW adapter.

8. Close the computer cabinet, connect the telephone cable into the CaprioSw adapter and the power cord to the pc.

Operating CaprioSW

- Call CaprioSW. After 6 rings you hear four beeps
- Enter three digits password (777 default)
- If the password is correct you hear four beeps otherwise you hear two beeps.
- If the password is not correct you can try three times.
- After you hear four beeps:

**I. DIAL 1 : Short Push
(Power Up/Down)**

**II. DIAL 2: Long Push
(Forced Power Down)**

III. DIAL 3: Change the password . After the beeps enter the new three digits password.